

# HP LaserJet Pro MFP M426dw

Impressive speed. Solid security.



Fast print, scan, and copy performance in such a small but robust package. This MFP finishes key tasks faster and guards against threats.<sup>1</sup> Original HP Toner cartridges with JetIntelligence give you more pages.<sup>2</sup>



## Highlights

- 38 ppm A4 black
- First page out from sleep/Auto-Off in 8 sec
- 50-sheet simplex scanning ADF; scan speed up to 26 ppm
- Leading duplex print speed of 30 ipm
- HP Auto-On/Auto-Off for low energy consumption
- 7.5 cm colour touchscreen with gesturing and apps
- Scan-to-email, -folder, -cloud, -USB
- LDAP, Private Printing, PIN Printing
- HP ePrint, AirPrint, Google Cloud Print, Wi-Fi Direct/NFC, Mopria-certified, Mobile Apps

## Speed through more tasks. Keep data protected.

- Scan digital files directly to email, USB, network folders, and the cloud with preloaded business apps.<sup>3</sup>
- Breeze through multipage documents with two-sided printing that's faster than the competition.<sup>1</sup>
- Grab pages and go – without waiting around. This MFP wakes up and prints faster than the competition.<sup>1</sup>
- Control access to print jobs and help keep printing safe with security features like LDAP authentication.

## Easy management. Efficient printing.

- Easily manage print jobs directly at the MFP – just tap and swipe the 7.6 cm (3-inch) touchscreen.<sup>4</sup>
- Easily print Microsoft® Word and PowerPoint® documents – now directly from your USB drive.<sup>5</sup>
- Easily manage devices and settings using HP Web Jetadmin with a suite of essential management features.<sup>6</sup>
- Print using less energy than competitors – enhanced by Original HP Toner cartridges with JetIntelligence.<sup>7</sup>

## More. Pages, Performance, and Protection.

- Get the most prints for your money – with Original HP High Yield Black Toner cartridges with JetIntelligence.<sup>2</sup>
- Count on professional quality at high speeds with precision black toner.
- Help ensure you're getting the authentic HP quality you paid for with innovative anti-fraud technology.
- Print right away with preinstalled toner cartridges. Replace them with optional high-yield cartridges.

## Stay connected with easy mobile printing options

- Easily print from a variety of smartphones and tablets – generally no setup or apps required.<sup>8</sup>
- Count on wireless direct printing in the office – from mobile devices – without accessing the company network.<sup>9</sup>
- Easily access, print, and share resources with Ethernet and wireless networking.<sup>10</sup>

Product walkaround

HP LaserJet Pro MFP M426dw shown

- 1. 50-sheet automatic document feeder (ADF)
- 2. Flatbed scanner: up to 216 x 297 mm paper
- 3. Intuitive 7.6 cm colour touchscreen (tilts up)
- 4. 150-sheet output bin
- 5. Easy-access USB port
- 6. Automatic two-sided printing
- 7. 100-sheet multipurpose tray 1
- 8. 250-sheet input tray 2
- 9. Power on/off button
- 10. Front door release button (access to HP JetIntelligence Toner cartridges)
- 11. Rear door (provides access to print path)
- 12. USB port for job storage and private printing
- 13. Hi-Speed USB 2.0 printing port
- 14. Ethernet network port
- 15. 1200 MHz processor
- 16. Dust cover for tray 2 — flips up when A4 is loaded



Accessories, Supplies and Support

Supplies	CF226A HP 26A Black Original LaserJet Toner Cartridge 3,100 pages
	CF226X HP 26X High Yield Black Original LaserJet Toner Cartridge 9,000 pages
Accessories	D9P29A HP LaserJet Pro 550-sheet Feeder Tray
Service and support	U8TQ9E HP 3 year Next business day LaserJet M426 MFP Hardware Support
	U8TR2E HP 3 year Next business day Exchange LaserJet M426 MFP SVC
	U8TR3E HP 3 year Return LaserJet M426 MFP Service
	U8TR4PE HP 1 year Post Warranty Next business day LaserJet M426 MFP Hardware Support
	U8TR5PE HP 1 year Post Warranty Next business day Exchange LaserJet M426 MFP SVC
	U8TR6PE HP 1 year Post Warranty Return LaserJet M426 MFP SVC

## Technical specifications

<b>Model</b>	<b>HP LaserJet Pro MFP M426dw</b>
<b>Product number</b>	F6W13A
<b>Functions</b>	Print, copy, scan
<b>Print</b>	
Print speed	Up to 38 ppm black (A4); Up to 30 ipm black duplex (A4)
First page out from ready <sup>1</sup>	As fast as 5.6 sec black (A4, ready)
First page out from sleep <sup>1</sup>	As fast as 8.0 sec
Print resolution	600 x 600 dpi, up to 4800 x 600 enhanced dpi black; HP FastRes 1200, HP ProRes 1200, 600 dpi
Print technology	Laser
Print Area	Print margins: Top: 5 mm; Bottom: 5 mm; Left: 4 mm; Right: 4 mm; Maximum print area: 215.9 x 355.6 mm
Print languages	HP PCL 5, HP PCL 6, HP Postscript Level 3 emulation, direct PDF (v1.7) printing, URF, PCLM, PWG, Native Office
Printer Smart Software Features	Auto-duplex printing; N-up printing; Collation; HP ePrint; Apple AirPrint™; Google Cloud Print; Wireless direct printing; Mopria-certified; HP Auto-On/Auto-Off; Intuitive 7.5 cm (3") touchscreen control panel; Print from Cloud using business apps on the control panel; HP JetAdvantage Private Print; Optional Job Storage with PIN printing (requires a purchase of separate USB flash drive); Print from USB; JetIntelligence Cartridge Technology
Monthly duty cycle	Up to 80,000 pages (A4); Recommended monthly page volume: 750 to 4,000 (print); 750 to 4,000 (scan)
Duplex printing	Automatic (standard)
Fonts and typefaces	84 scalable TrueType fonts
SureSupply supported	Yes
<b>Processor speed</b>	1200 MHz
<b>Connectivity</b>	
Standard	1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network; 1 Wireless 802.11b/g/n; Easy-access USB
Supported network protocols	TCP/IP, IPv4, IPv6; Print: TCP-IP port 9100 Direct Mode, LPD (raw queue support only), Web Services Printing, HP ePrint, Apple AirPrint™, Google Cloud Print 2.0, Mopria, FTP Print, IPP Print; Discovery: SLR, Bonjour, Web Services Discovery; IP Config: IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Statefull via DHCPv6), SSL Security and Certificate management; Management: SNMPv1, SNMPv2, SNMPv3, HTTP/HTTPS, Syslog, FTP FW Download
<b>Network ready</b>	Standard (built-in Ethernet, Wi-Fi) (operates as both an AP, with Wi-Fi Direct, and STA)
<b>Hard disk</b>	No
<b>Memory</b>	Standard: 256 MB; Maximum: 256 MB
<b>Copy</b>	
Copier settings	Lighter/Darker; ID copy; Optimise; Maximum number of copies: Up to 99 copies; Copy resolution: 600 x 600 dpi Reduce/Enlarge: 25 to 400%
Copy speed	Up to 38 cpm black (A4)
<b>Scan</b>	
Scanner specifications	Scanner type: Flatbed, ADF; Scan technology: Contact Image Sensor (CIS); Scan input modes: For scan software (included in the box) support: Windows [JPG, RAW(BMP), PDF, TIFF, PNG, RTF] and Mac [JPG, JPG-2000, TIFF, PNG, PDF, searchable PDF, RTF, TXT]; Twain version: Version 1.9 (legacy OS); Version 2.1 (Windows 7 or higher); Duplex ADF scanning: No; Scan size maximum (flatbed, ADF): 297 x 216 mm; Optical scan resolution: Up to 1200 x 1200 dpi
Scan file format	Flatbed, ADF
Scan speed <sup>9</sup>	Up to 21 ppm/26 ipm (monochrome)
Scannable area	Flatbed: Minimum media size: 48.8 x 48.8 mm; Maximum media size: 297 x 216 mm Scannable area (ADF): Minimum media size: 102 x 152 mm; Maximum media size: 216 x 355.6 mm
Scanner Advanced Features	Scan-to-email; Scan-to-Cloud; Scan-to-USB; Scan-to-network folder; LDAP email lookup; Simplex scanning ADF (50-sheet)
Bit depth/ Grey scale levels	24-bit / 256
Digital sending	Standard: Scan-to-email; Scan-to-network folder; Scan-to-Cloud
Recommended monthly scan volume	750 to 4,000
<b>Fax</b>	
Fax	No
Telecom compliance	Wireless telecommunications: EU (R&TTE Directive 1999/5/EC); EN 301 489-1 V1.9.2; EN 301 489-17 V2.2.1; EN 300 328 V1.8.1; IEC 62311:2007; EN 62311:2008
<b>Paper handling</b>	
Media types	Paper (plain, EcoEFFICIENT, light, heavy, bond, coloured, letterhead, preprinted, prepunched, recycled, rough), envelopes, labels, transparencies
Paper size	Custom metric: Tray 1: 76.2 x 127 to 215.9 x 355.6 mm; Tray 2, 3: 104.9 x 148.59 to 215.9 x 355.6 mm Supported metric: Tray 1: A4, A5, A6, B5 (JIS), Envelope B5, Envelope C5, Envelope DL, custom size; Tray 2 & Tray 3: A4, A5, A6, B5 (JIS), custom size ADF: A4; 127 x 127 to 216 x 355.6 mm
Paper handling	Standard input: 100-sheet tray 1, 250-sheet input tray 2 Standard output: 150-sheet output bin Optional/Input: Optional third 550-sheet tray ADF: Standard, 50 sheets
Input capacity	Tray 1: Sheets: 100; Envelopes: 10 Tray 2: Sheets: 250 Tray 3: Sheets: 550 (optional) Maximum: Up to 900 sheets (with optional 550-sheet tray)
Output capacity	Standard: Up to 150 sheets; Up to 10 envelopes; Up to 75 sheets; Transparencies Maximum: Up to 150 sheets Envelopees: Up to 10 envelopes Transparencies : Up to 75 sheets
Paper weight	Tray 1: 60 to 175 g/m²; Tray 2, optional 550-sheet tray 3: 60 to 120 g/m² ADF: 60 to 90 g/m²
<b>Compatible operating systems</b>	Windows OS compatible with In-Box Driver: Windows 10 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 8/8.1 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 7 all 32 & 64-bit editions, Windows Vista all 32-bit editions (Home Basic, Premium, Professional, etc.); Windows OS compatible with Universal Print Driver (from <a href="http://www.HP.com">http://www.HP.com</a> ): Windows 10 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 8/8.1 all 32 & 64-bit editions (excluding RT OS for tablets), Windows 7 all 32 & 64-bit editions, Windows Vista all 32 & 64-bit editions (Home Basic, Premium, Professional, etc.); Mac OS (HP print drivers available from <a href="http://www.HP.com">http://www.HP.com</a> and Apple Store): OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite; Mobile OS (In-OS drivers): iOS, Android, Windows 8/8.1/10 RT; Linux OS (In-OS HPLIP, auto install): BOSS (3.0, 5.0), DEBIAN (6.0, 6.0.1, 6.0.2, 6.0.3, 6.0.4, 6.0.5, 6.0.6, 6.0.7, 6.0.8, 6.0.9, 6.0.10, 7.0, 7.1, 7.2, 7.3, 7.4, 7.5, 7.6), FEDORA (17, 18, 19, 20), LINUS MINT (13, 14, 15, 16, 17), SUSE LINUX (12.2, 12.3, 13.1), UBUNTU (10.04, 11.10, 12.04, 12.10, 13.04, 13.10, 14.04, 14.10); Linux OS (In-OS HPLIP, manual install): MANDRIVA LINUX (2010.0, 2011.0), MEPIS (6.0, 6.5, 7.0, 8.0), PCLINUXOS (2006.0, 2006, 2007.0, 2007, 2008.0, 2008, 2009.0, 2009), RED HAT (8.0, 9.0), RED HAT ENTERPRISE LINUX (5.0, 6.0, 7.0), SLACKWARE LINUX (9.0, 9.1, 10.0, 10.1, 10.2, 11, 12, 12.1), GOS (8.04.1), IGO5 (1.0), LIMPUS LINUX (9.4, 9.5), LINUX FROM SCRATCH (6); Other OS: UNIX

<b>Model</b>	<b>HP LaserJet Pro MFP M426dw</b>
<b>Product number</b>	F6W13A
<b>Compatible network operating systems</b>	Windows OS compatible with In-Box Driver: Windows Server 2008 R2 64-bit (SP1) Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008 32 & 64-bit (SP2) Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2003/2003 R2 32-bit (SP1/SP2) Standard/Enterprise (+ Cluster & Terminal Services); Windows OS compatible with Universal Print Driver (UPD) or product-specific drivers from <a href="http://www.hp.com">http://www.hp.com</a> : Windows Server 2012/2012 R2 64-bit Standard/Foundation/Essentials/Datacenter (+ Cluster & Terminal Services), Windows Server 2008/2008 R2 32 & 64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2003/2003 R2 32 & 64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), MS Windows Server 2012 R2 Terminal Services, Citrix XenApp 7.5, Citrix XenDesktop 7.0, Citrix XenDesktop 7.5, MS Windows Server 2012 Terminal Services, Citrix XenApp 7.5, Citrix XenDesktop 7.0, Citrix XenDesktop 7.5, MS Windows Server 2008 R2 SP1 Terminal Services, Citrix XenApp 6.0, Citrix XenApp 6.5, Citrix XenApp 7.5, Citrix XenDesktop 5.6, Citrix XenDesktop 7.0, Citrix XenDesktop 7.5, MS Windows Server 2008 R2 Terminal Services, Citrix XenApp 6.0, Citrix XenApp 6.5, Citrix XenDesktop 5.6, MS Windows Server 2008 Terminal Services, Citrix XenApp 5.0, Citrix XenApp 5.0 Feature Pack 2 & 3, MS Windows Server 2003 Terminal Services, Citrix Presentation, ServerTM 4.5, Citrix Presentation Server 4.0, MS Windows Server 2003 Terminal Services, Citrix Presentation Server 4.5, Citrix Presentation Server 4.0, Citrix MetaFrame® Presentation Server 3.0, Citrix MetaFrame XP Presentation Server (Feature Release 1, 2 and 3); Novell Servers ( <a href="http://www.novell.com/iprint">http://www.novell.com/iprint</a> ): Novell Open Enterprise Server 11/SP1 /SP2, Novell Open Enterprise Server 2 for Linux, NetWare 6.5/SP8; Novell Clients ( <a href="http://www.novell.com/iprint">http://www.novell.com/iprint</a> ): Novell iPrint Client v5.4 for Vista, Win 7 & Win 8 (32 & 64-bit), Novell iPrint Client v5.4 for Win XP (32 & 64-bit)
<b>Mobile printing capability</b>	HP ePrint; Apple AirPrint™; Wireless direct printing; Mopria-certified; Google Cloud Print 2.0; Mobile apps
<b>Minimum system requirements</b>	Windows: Windows 10 (32 & 64-bit), Windows 8/8.1 (32 & 64-bit), Windows 7 (32 & 64-bit): 1 GHz processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port; Windows Vista (32-bit): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port; Windows Server 2008 (64-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (x64) processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port; Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), Windows Server 2008 (32-bit) (SP1 or greater): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or network port Mac: OS X 10.8 Mountain Lion, OS X 10.9 Mavericks, OS X 10.10 Yosemite, Internet, USB, 1 GB available hard disk space, OS compatible hardware (for OS hardware requirements see <a href="http://www.apple.com">http://www.apple.com</a> )
<b>Software included</b>	Windows 7: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Update, HP Device Toolbox, HP Printer Status and Alerts, HP Product Improvement Study, HP Scan App and Driver, Reconfigure your HP Device, Scan to Email Wizard, Scan to Network Folder Wizard, Warranty and Legal Guide, User Guide; Windows 8+: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Scan App and Driver, Warranty and Legal Guide, User Guide, Reconfigure your HP Device; Windows XP, Windows Vista and associated servers: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Scan App and Driver, Warranty and Legal Guide, User Guide; Mac OS: Welcome Screen (directs users to <a href="http://www.hp.com">http://www.hp.com</a> or OS App Source for LaserJet Software)
<b>Security management</b>	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPv1 & SNMPv2 community password change; HP ePrint: HTTPS with certificate validation, HTTP Basic Access Authentication, SASL authentication; LDAP authentication and authorization; Firewall and ACL; SNMPv3, 802.1X, Secure Boot, authentication via WEP, WPA/WPA2 Personal, WPA2 Enterprise; Encryption via AES or TKIP
<b>Printer management</b>	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac); HP Device Toolbox
<b>Control panel</b>	7.5 cm (3") touchscreen Colour Graphic Display (CGD)
<b>Dimensions / Weights</b>	
Printer dimensions	Minimum: 420 x 390 x 323 mm Maximum: 430 x 634 x 325 mm
Package dimensions (W x D x H)	497 x 398 x 490 mm
Printer Weight	12.86 kg
Package weight	15.5 kg
<b>Operating environment</b>	Temperature: 15 to 32.5°C, Humidity: 30 to 70% RH
<b>Storage</b>	Temperature: -20 to 40°C, Humidity: 10 to 90% RH
<b>Acoustics<sup>3</sup></b>	Acoustic power emissions: 6.8 B(A) (printing at 38 ppm); Acoustic pressure emissions: 55 dB(A)
<b>Power<sup>4</sup></b>	Requirements: Input voltage: 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz) Consumption: 583 watts (print/copy), 9.1 watts (ready), 2.7 watts (sleep), 0.7 watts (Auto-On/Auto-Off, via USB connectivity), 0.1 watts (off) Typical Electricity Consumption (TEC): 1.660 kWh/Week (Blue Angel), 1.847 kWh/Week (Energy Star) Power supply type: Built-in power supply
<b>Energy savings feature technology</b>	Instant-on Technology; HP Auto-On/Auto-Off Technology
<b>Certifications</b>	CISPR 22:2008/EN 55022:2010 (Class B); EN 61000-3-2:2006 +A1:2009 +A2:2009; EN 61000-3-3:2008; EN 55024:2010 ENERGY STAR® certified; Blue Angel; EPEAT® Silver
<b>Warranty</b>	One-year warranty, return to HP Authorized Service Provider
<b>What's in the box</b>	HP LaserJet Pro MFP M426dw; Presinstalled HP 26A Black LaserJet Toner Cartridge (3,100 pages); Getting Started Guide; Setup poster; Support flyer; Warranty guide; Printer documentation and software on CD-ROM; Power cord; USB cable; Built-in duplexer
<b>Replacement cartridges<sup>5</sup></b>	HP 26A Black LaserJet Toner Cartridge (3,100 pages) CF226A; HP 26X Black LaserJet Toner Cartridge (9,000 pages) CF226X
<b>Wireless</b>	Yes, built-in Wi-Fi; Authentication via WEP, WPA/WPA2, WPA Enterprise; encryption via AES or TKIP; WPS; Wi-Fi Direct

## Footnotes

<sup>1</sup> Based on HP internal testing of top three leading competitors' first page out from sleep mode and duplex print and copy speed completed 8/2015. Subject to device settings. Actual results may vary. For details see <http://www.hp.com/go/ljclaims>.; <sup>2</sup> Based on cartridge yields for HP 80X compared with HP 26X Original HP LaserJet Toner Cartridges. For more information, see <http://www.hp.com/go/learnaboutsupplies>.; <sup>3</sup> Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see <http://www.hpconnected.com>.; <sup>4</sup> Requires a wireless access point and an Internet connection to the printer. Services require registration. App availability varies by country, language, and agreements and requires a firmware upgrade. For details, visit <http://www.hpconnected.com>.; <sup>5</sup> Microsoft and PowerPoint are U.S. registered trademarks of the Microsoft group of companies. Feature works with Microsoft Word and PowerPoint 2003 and later. Only Latin language fonts are supported.; <sup>6</sup> HP Web Jetadmin is free and available for download at <http://www.hp.com/go/webjetadmin>.; <sup>7</sup> Based on HP testing using the ENERGY STAR® program's Typical Electricity Consumption (TEC) method or as reported in energystar.gov of top three leading competitors as of 8/2015. Actual results may vary. For details see <http://www.hp.com/go/ljclaims>.; <sup>8</sup> Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may also be required. Some features require purchase of an optional accessory. Learn more at <http://www.hp.com/go/mobileprinting>.; <sup>9</sup> Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at <http://www.hp.com/go/businessmobileprinting>.; <sup>10</sup> Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections.

## Technical specifications disclaimers

<sup>1</sup> Measured using ISO/IEC 17629, excludes first set of test documents. For more information, see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the input voltage, system configuration, software application, driver, and document complexity.; <sup>2</sup> With 26A cartridge (F6W13A) or 26X cartridge (F6W16A).; <sup>3</sup> Configuration tested: base model, simplex printing, A4 paper at an average of 38 ppm, active scan at 26 ppm.; <sup>4</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.; <sup>5</sup> Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit <http://www.hp.com/go/learnaboutsupplies>.; <sup>6</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.; <sup>7</sup> HP recommends that the number of pages per month of imaged output be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.; <sup>8</sup> First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information, see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.; <sup>9</sup> Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.; <sup>10</sup> For scan software (included in the box) support: Windows [JPG, RAW(BMP), PDF, TIFF, PNG, RTF] and Mac [JPG, JPG-2000, TIFF, PNG, PDF, RTF, TXT]; <sup>11</sup> Not all "Compatible Operating Systems" are supported with inbox software. Full solution software available only for Windows 7 and newer. Legacy Windows Operating Systems (XP, Vista, and equivalent servers) get print drivers only. Windows RT OS for tablets (32 & 64-bit) uses a simplified HP print driver built into the RT OS. UNIX modelscripts are available on HP.com (modelscripts are printer drivers for UNIX operating systems). Linux systems use in-OS HPLIP software. HP Software for Mac is no longer included on the CD, but can be downloaded from <http://www.hp.com> - the Mac driver and Mac Utility are installed for Mac operating systems.; <sup>12</sup> HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. For more information, visit <http://www.hp.com/go/SureSupply>. Only available with Original HP supplies. Internet access required.; <sup>13</sup> With 26A cartridge.; <sup>15</sup> Best Typical Electricity Consumption (TEC) rating represents the typical electricity consumed by a product during 1 week, measured in kilowatt-hours (kWh). For Best TEC, the product configuration is Wi-Fi disabled, 1 minute sleep delay, and connected to LAN.



<http://www.hp.com/uk>

The product could differ from the images shown. © Copyright 2015 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

Published in EMEA 08/15 EEE

